# **STEP & TOUCH VOLTAGE MEASUREMENT**









www.eurosmc.com

# LET-60-VPC / LET-500-VPC





#### Step & Touch Voltage measurement

#### **APPLICATION**

These sets are designed to test ground circuit measurements, in what is called voltage in step and touch according to IEC standards used in some countries.

## DESCRIPTION

The sets contain two distinct functions, the current injection and the voltage measurement.

In the injection of current, a variable autotransformer of current regulation is connected to a current producer transformer with various ranges of output. The current produced is measured with a shunt system connected to a digital instrument. This system of current injection makes possible to shift the current 180° in order to avoid possible stray current over the ground.

The voltage in step and touch measurement is made up with a digital voltmeter of 3 1/2 digits with a input designed so that the ohm resistance will be 1 K $\Omega$ . The precision of this set is ±1%.

# TECHNICAL SPECIFICATIONS

	LET-60-VPC	LET-500-VPC
Voltage supply	220V 50/60 Hz	
Outputs	0-6A/0-1000V 0-12A/0-500V 0-24A/0-250V 0-60A/0-100V	0-50A / 0-1000V
Nominal Power	6KVA in continuous service	50KVA in continuous service
VOLTAGE MEASUREMENT		
	3 1/2 dígits LED type	
Measurement ranges	0,2V, 2V, 20V, 200V	
Internal resistance	$1 K\Omega$ in all ranges	
Precision	±1% F.E.	
CURRENT OUTPUT MEASUREMENT		
Digital amperemeter	3 1/2 dígits LED type	
Measurement ranges	6A, 20A, 30A, 60A	0-199.9A
GENERAL		
Dimensions	Height: 350 mm / 14" Width: 350 mm / 14" Depth: 700 mm / 28"	Height: 1000 mm / 40" Width: 700 mm / 28" Depth: 670 mm / 27"
Weight	135 Kg / 230 lb	350 Kg / 770 lb.

# **CHARACTERISTICS**

- Accessories for measurements incorporated.
- Inversion of current output.
- Current measurement: ±0.5%.
- Voltage measurement: ±1%.

#### **ACCESSORIES INCLUDED**

- 2 grounding electrods with 200x100 mm section and 25 Kg. (each one).
- 3 rolls of 50 m cable for test leads.
- Instruction manual.
- Calibration certificate.

C

VPCCCEN.

DISTRIBUTED BY: